
Carrier IP Networks: MPLS



Raj Jain
Washington University in Saint Louis
Saint Louis, MO 63130
Jain@cse.wustl.edu

These slides and audio/video recordings of this class lecture are at:
http://www.cse.wustl.edu/~jain/cse5700-25/

Student Questions

©2025 Raj Jain



Overview


1. Plesiochronous Digital Hierarchy
2. Multiprotocol Label Switching (MPLS)
3. MPLS over Ethernet
4. Ethernet over MPLS

Student Questions

©2025 Raj Jain

Plesiochronous Digital Hierarchy (PDH)


- Plesios + Synchronous = Near synchronous
- Phone Line = 64 kbps = 1 User channel
- North America
  - T1 = 1.544 Mbps = 24 User channels
  - T2 = 6.312 Mbps = 96 Channels
  - T3 = 44.736 Mbps = 480 Channels
- Europe:
  - E1 = 2.048 Mbps = 32 Channels
  - E2 = 8.448 Mbps = 128 Channels
  - E3 = 139.264 Mbps = 2048 Channels




Student Questions

©2025 Raj Jain

SONET/SDH






- SONET=Synchronous optical network
- Standard for digital optical transmission
- Standardized by ANSI and then by ITU
  ⇒ Synchronous Digital Hierarchy (SDH)
- Protection: Allows redundant Lines or paths
- Fast Restoration: 50ms using rings
- Sophisticated management
- Ideal for Voice: No queues. Guaranteed delay
- Fixed Payload Rates: OC1=51.84 Mbps, OC3=155M, OC12=622M, OC48=2.4G, OC192=9.5G
  Rates do not match data rates of 10M, 100M, 1G, 10G
- Static rates not suitable for bursty traffic
- One Payload per Stream ⇒ High Cost


Student Questions

©2025 Raj Jain

Multiprotocol Label Switching (MPLS)




- Allows virtual circuits in IP Networks (May 1996)
- Each packet has a virtual circuit number called 'label.'
- Label determines the packet's queuing and forwarding
- Circuits are called Label Switched Paths (LSPs)
- LSPs have to be set up before use
- Allows traffic engineering



Student Questions

©2025 Raj Jain

Label Switching Example




Student Questions

©2025 Raj Jain

MPLS Concepts

- **Forwarding Equivalence Class (FEC)**: All packets with the same top label
- **Label Switched Path (LSP)**: End-to-end path from label push to label pop
- **Label Edge Router (LER)**: Routers that push labels at the beginning of LSP and pop at the end
- **Label Switch Router (LSR)**: Core routers that forward using the label




- **Label Forwarding Information Base (LFIB)**: Forwarding table created using routing protocols, e.g., OSPF, BGP
- **Label Distribution Protocol (LDP)**: To discover other MPLS routers and set up LSPs.
- **Resource ReSerVation Protocol with Traffic Engineering (RSVP-TE)**: OSPF and BGP are alternatives.

Student Questions


©2025 Raj Jain

Label Stacks

- Labels are pushed/popped as they enter/leave the MPLS domain



- Routers in the interior will use Interior Gateway Protocol (IGP) labels. Border gateway protocol (BGP) labels outside.
- The bottom label may indicate protocol (0=IPv4, 2=IPv6)





Student Questions

©2025 Raj Jain

MPLS Label Stacking

- Label stacking allows:
  - Multiple levels of carriers.
  - Multiple VPNs in a single LSP
  - Multiple types of traffic in a single LSP





Student Questions

©2025 Raj Jain

MPLS Traffic Engineering

- MPLS paths can be provisioned to follow a specific path (no need to use the shortest path)
- Resources on the path can be reserved
- Multiple parallel LSPs can be established between the same pair of nodes
- Fault recovery via shifting traffic to standby LSPs

Student Questions

©2025 Raj Jain

MPLS Forwarding Tables

- Interface numbers are in circles. Label IDs are in rectangles.

R6


In Interface	In Label	Dest.	Out Interface	Out Label
-	None	A	0	17
-	None	D	0	18

R4

In Interface	In Label	Dest.	Out Interface	Out Label
3	17	-	0	20
3	18	-	0	22
2	24	-	1	18

R3

In Interface	In Label	Dest.	Out Interface	Out Label
2	20	-	1	17
2	22	-	0	None



R5

In Interface	In Label	Dest.	Out Interface	Out Label
-	None	A	0	24

R2

In Interface	In Label	Dest.	Out Interface	Out Label
1	18	-	0	24

R1

In Interface	In Label	Dest.	Out Interface	Out Label
2	17	-	0	None
1	24	-	0	None

Student Questions

©2025 Raj Jain


MPLS Forwarding Tables (Cont)

- The tables are per interface, not per router.
- The same label #s can be used in different interfaces of the same router. For example, See Router R3 in the "Label Switching Example" slide.
- Only one direction of circuits is shown for clarity.
  - There is an equal number of reverse circuits that have their own labels unrelated to forward labels.
- Out Label=None ⇒ MPLS Tag is removed.
  In Label=None ⇒ Packet arrives with no MPLS tag.

Student Questions

©2025 Raj Jain

IP over MPLS over Ethernet





- Allows 2^{20} Label switched paths (LSP)
- Each path can have reserved capacity ⇒ Guaranteed **QoS**
- Explicit paths can be designed for specific traffic going to the same destination ⇒ **Traffic Engineering**
- Alternate paths are used if anything on the primary path fails ⇒ **Fast Reroute** ⇒ MPLS became a very popular

Student Questions

©2025 Raj Jain

Pseudo Wire: L2 Circuits over IP






Student Questions

©2025 Raj Jain

Ethernet over PWE3 over MPLS




- Pseudo-Wire Emulation Edge-to-Edge (PWE3)
- Multiple pseudo-wires per MPLS LSP
  ⇒ Core routers use the outer "*path*" label and not the inner "*VC*" label
- PW (VC) label format is the same as the MPLS label with End-of-Stack=1 and TTL=1. PW label is inserted/removed at the edge.
- Payload ID (PID): 5=Untagged Ethernet, 4=VLAN tagged, …
- 4⇒VLAN tags by carriers and customers may or may not be relevant for forwarding. Determined administratively by PE.
- Flags: Payload specific. FRG: Used for fragmentation
- Pause frames are obeyed locally. Not transported.

Student Questions

©2025 Raj Jain

Summary



1. SONET, SDH, and PDH networks were designed for voice traffic
2. Carriers use MPLS to provide reliability and throughput guarantees similar to their previous networks
3. MPLS-TP is designed with OAM required for carriers

Student Questions


Homework 6: MPLS

- [28 points] The next figure shows the flows on an MPLS network with the reverse direction flows. Using the Labels shown, fill in all the tables.

Student Questions

Homework 6D (Cont)

- Interface numbers are in circles. Label IDs are in rectangles.



R6

In Interface	In Label	Dest.	Out Interface	Out Label

R4

In Interface	In Label	Dest.	Out Interface	Out Label
		-		

R3

In Interface	In Label	Dest.	Out Interface	Out Label

R5

In Interface	In Label	Dest.	Out Interface	Out Label

R2

In Interface	In Label	Dest.	Out Interface	Out Label

R1

In Interface	In Label	Dest.	Out Interface	Out Label

Student Questions

Reading List

- Karthik Ramasamy, Deep Medhi, "Network Routing," 2nd Edition, Morgan Kaufmann, September 2017, ISBN: 9780128008294 (Safari Book), Chapter 22: MPLS.

Student Questions

©2025 Raj Jain

References

- Krzysztof Grzegorz Szarkowicz, Antonio Sanchez Monge, "MPLS in the SDN Era," O'Reilly Media, Inc., December 2015, 920 pp., ISBN:978-1-4919-0545-6 (Safari Book).

Student Questions

©2025 Raj Jain

Wikipedia Links

- http://en.wikipedia.org/wiki/Label-switched_path
- http://en.wikipedia.org/wiki/Link_protection
- http://en.wikipedia.org/wiki/MPLS-TP
- http://en.wikipedia.org/wiki/Multiprotocol_Label_Switching
- http://en.wikipedia.org/wiki/Operations,_administration_and_management
- http://en.wikipedia.org/wiki/Optical_Carrier_transmission_rates
- http://en.wikipedia.org/wiki/Optical_Transport_Network
- http://en.wikipedia.org/wiki/Path_protection
- http://en.wikipedia.org/wiki/Plesiochronous_digital_hierarchy
- http://en.wikipedia.org/wiki/Provider_Backbone_Bridge_Traffic_Engineering
- http://en.wikipedia.org/wiki/Pseudo-wire
- http://en.wikipedia.org/wiki/Synchronous_optical_networking
- http://en.wikipedia.org/wiki/Traffic_policing

Student Questions

©2025 Raj Jain

Acronyms

- ANSI — American National Standards Institute
- BGP — Border Gateway Protocol
- CE — Customer Edge
- FCS — Frame Check Sequence
- FEC — Frame Equivalence Class
- FRG — Fragment Bit
- GMPLS — Generalized Multi-Protocol Label Switching
- GRE — Generic Routing Encapsulation
- ID — Identifier
- IGP — Interior Gateway Protocol
- IP — Internet Protocols
- ITU — International Telecommunications Union
- LDP — Label Distribution Protocol
- LER — Label Edge Router

Student Questions

©2025 Raj Jain

Acronyms (Cont)

- LFIB Label Forwarding Information Base
- LSE Label Stack Entry
- LSP Label Switched Paths
- LSR Label Switching Router
- MPLS Multi-Protocol Label Switching
- OAM Operation, Administration and Maintenance
- OC Optical Carrier
- OSPF Open Shortest Path First
- PDH Plesiochronous Digital Hierarchy
- PE Provider Edge
- PID Protocol ID
- PW Pseudo-Wire
- PWE3 Pseudo-Wire Emulation Edge-to-Edge

Student Questions

©2025 Raj Jain

Acronyms (Cont)

- QoS Quality of Service
- SDH Synchronous Digital Hierarchy
- SDN Software Defined Networking
- SONET Synchronous optical network
- TE Traffic Engineering
- TP Transport Profile
- TTL Time to Live
- VC Virtual Circuit
- VLAN Virtual Local Area Network
- VPN Virtual Private Network

Student Questions

©2025 Raj Jain

Scan This to Download These Slides



Raj Jain
http://rajjain.com

http://www.cse.wustl.edu/~jain/cse5700-25/m_05cip.htm

Student Questions

©2025 Raj Jain

Related Modules



CSE567M: Computer Systems Analysis (Spring 2013),
https://www.youtube.com/playlist?list=PLjGG94etKypJEKjNAa1n_1X0bWWNyZcof

CSE473S: Introduction to Computer Networks (Fall 2011),



https://www.youtube.com/playlist?list=PLjGG94etKypJWOSPMh8Azcgy5e_10TiDw



Wireless and Mobile Networking (Spring 2016),
https://www.youtube.com/playlist?list=PLjGG94etKypKeb0nzyN9tSs_HCd5c4wXF

CSE571S: Network Security (Fall 2011),



https://www.youtube.com/playlist?list=PLjGG94etKypKvzfVtutHcPFJXumyyg93u



Video Podcasts of Prof. Raj Jain's Lectures,
https://www.youtube.com/channel/UCN4-5wzNP9-ruOzQMs-8NUw

Student Questions

©2025 Raj Jain